



## FiberLink® 4040 Audio Series



### FEATURES

**Transmits over one multimode or single mode fiber at 850, 1310 or 1550 nm**

No adjustments; pure digital processing and transmission

24 bit/96 kHz sampling; maximum audio level +24 dBu

20 Hz to 20 kHz frequency response

Line level, balanced or unbalanced audio operation

Indicator LEDs monitor audio signals and power

Wide range power supply allows operation from low voltage AC and DC sources

Card version fills one slot in 6000A card cage

System consists of transmitter and receiver unit; card or box version

Each end, plus power supply, must be purchased separately

### Four independent audio channels digitally transmitted over one fiber

The FiberLink 4040 Series digitally transmits four independent audio channels over one multimode or single mode fiber at 850, 1310 or

1550 nm. It is ideal for rental, staging, education and broadcast applications.



## FiberLink 4040 Audio Series

### SPECIFICATIONS

#### General Specifications

LED Indicators	Power; Audio Present (per channel); Alarm LED (card version only)
Power Requirements*	9-24 volts AC or DC, 5 watts
Operating Temperature Range	-35° to +60° C
Relative Humidity	10%-90% (non-condensing)
Optical Connectors	ST
Operating Wavelength	850, 1310 or 1550 nm
Physical Size	6.5 W x 1.15 H x 8 L (inches) 165 W x 29 H x 203 L (mm)
Weight	approx. 1 lb.; 0.45 kg
Slots Filled in 6000A Card Cage	1
MTBF	83,000 Hours

\* For operation from 95-250VAC, 50/60Hz, a PDPS-1 plug-in adapter is required.

#### Audio Specifications

Number of Audio Channels	4, balanced or unbalanced
Frequency Response	+0/-0.5 dB, 20 Hz - 20 kHz
Bits-per-Sample/Sampling Rate	24 bits; 96 kHz
Maximum Audio Level	+24 dBu
SNR (A-Weighted)	95 dB
THD+N	0.002%, 20 Hz - 20 kHz
Channel Phase Differential	+0.1°
System Latency	200 us + fiber cable propagation delay (typically 5 us/km of fiber)
Crosstalk	Min. 95 dB (1 kHz)
Input Impedance	600 Ohms terminated; >24 k Ohms unterminated
Output Impedance	50 Ohms
Audio Connectors	Removable screw terminal
Switches	Dip switches to select input termination, balanced or unbalanced input/output. Selectable on a per-channel basis

#### Operating Loss Budget & Maximum Usable Distance\*

Wavelength	Loss (dB)	Distance (km)
850 MM	0-20	0-2
1310 MM	0-25	0-10
1310 SM	0-23	0-55
1550 SM	0-25	0-80

SM = Single Mode Fiber

MM = MultiMode Fiber

\*Distance specifications are only approximate and are not guaranteed. Operating loss budget must not be exceeded.



UPDATED 07/30/2016



Schedule  
Contract GS-03F-018CA

All specifications subject to change without notice. ©2016

#### Ordering Information

Part Number	Description	Fiber Cores
4040-ByS	Transmitter, Box Version	1
4040-CyS	Transmitter, Card Version	1
4041-ByS	Receiver, Box Version	1
4041-CyS	Receiver, Card Version	1
PDPS-1-pp	Power Supply	

#### Power Supply Suffix Codes (pp) for AC Line Cord:

NA - North America AU - Australia EU - Europe  
JP - Japan UK - United Kingdom

#### Part Number Suffix Codes:

y: 1 - 850 nm Multimode  
3 - 1310 nm Multimode  
7 - 1310 nm Single Mode  
9 - 1550 nm Single Mode

#### Sales



T: +1 978-263-5775  
sales@artel.com  
customer@artel.com  
www.artel.com